
























REGAL ERALIGHT


Ref: S3492027574ERA3406DR
REGAL ERALIGHT 75W 4000K LED NEGRO SIM EXT 160º 1-10V

| | | |
|---|---|---|
|  EXTERIOR |  67,5 W LED 75 W Sistema |  8739 lm LED 7945 lm Sistema |
|  SUPERFICIE |  Driver incluido (SPD10KV) |  0 |
|  Garantía 5 AÑOS |  1-10V |  mm |
| |  IP65 |  70 |
| |  08 |  I |
|  MIDPOWER |  SIM EXT 160 |  L80B10 50000h 85°C L70B50 70000h 85°C |
|  220-240V |  4000K |  -20º+35ºC |
|  50-60Hz |  0 (Riesgo fotobiológico) |  18Kg |
| | |  Ancho Ø520 mm Largo mm Alto 850 mm |

Tolerancias: +-7% flujo LED / +- 10% potencia luminaria

CURVAS

