























MAGEC ERALIGHT


Ref: S3496585574ERA3406DR

MAGEC ERALIGHT 55W 4000K LED GRIS SABLE SIM EXT 160°DRIVER REG 1-10V

 EXTERIOR	 49,5 W LED 55 W Sistema	 6868 lm LED 6176 lm Sistema
 SUPERFICIE	 Driver incluido (SPD10KV)	 -
 Garantía 5 años	 DRIVER REG 1-10V	 - mm
	 IP65	 70
	 10	 II
 Mid Power	 SIM EXT 160	 L80B10 50000h 85°C L70B50 70000h 85°C
 220-240V	 4000K	 -20 +35°
 50/60Hz	 0 (Riesgo fotobiológico)	 6Kg



Ancho 320 mm
Largo VERT 745mm/ HORZ 62 mm
Alto VERT 262mm/HORZ 130 mm

Tolerancias: +-7% flujo LED / +- 10% potencia luminaria

CURVAS

