























# MAGEC ERALIGHT


**Ref:** S3496583475ERA3405DR

**MAGEC ERALIGHT 34W 5000K LED GRIS SABLE ASIM EXTºDRIVER REG 1-10V**

 EXTERIOR	 30,6 W LED 34 W Sistema	 5062 lm LED 4685 lm Sistema
 SUPERFICIE	 Driver incluido (SPD10KV)	 -
 Garantía 5 años	 DRIVER REG 1-10V	 - mm
	 IP65	 70
	 10	 II
 Mid Power	 ASIM EXT	 L80B10 50000h 85°C L70B50 70000h 85°C
 220-240V	 5000K	 -20 +35º
 50/60Hz	 0 (Riesgo fotobiológico)	 6Kg



Ancho 320 mm  
Largo VERT 745mm/ HORZ 62 mm  
Alto VERT 262mm/HORZ 130 mm

Tolerancias: +-7% flujo LED / +- 10% potencia luminaria

## CURVAS

