
























REGAL ERALIGHT


Ref: S3492023574ERA3406
REGAL ERALIGHT 35W 4000K LED NEGRO SIM EXT 160° ON/OFF

 EXTERIOR	 31,5 W LED 35 W Sistema	 4858 lm LED 4417 lm Sistema
 SUPERFICIE	 Driver incluido (SPD10KV)	 0
 Garantía 5 AÑOS	 ON/OFF	 mm
	 IP65	 70
	 08	 I
 MIDPOWER	 SIM EXT 160	 L80B10 50000h 85°C L70B50 70000h 85°C
 220-240V	 4000K	 -20°+35°C
 50-60Hz	 0 (Riesgo fotobiológico)	 18Kg
		 Ancho Ø520 mm Largo mm Alto 850 mm

Tolerancias: +-7% flujo LED / +- 10% potencia luminaria

CURVAS

