
























REGAL ERALIGHT


Ref: S3492029073ERA3406DR
REGAL ERALIGHT 90W 3000K LED NEGRO SIM EXT 160º 1-10V

 EXTERIOR	 81 W LED 90 W Sistema	 10025 lm LED 9114 lm Sistema
 SUPERFICIE	 Driver incluido (SPD10KV)	 0
 Garantía 5 AÑOS	 1-10V	 mm
	 IP65	 70
	 08	 l
 MIDPOWER	 SIM EXT 160	 L80B10 50000h 85°C L70B50 70000h 85°C
 220-240V	 3000K	 -20º+35°C
 50-60Hz	 0 (Riesgo fotobiológico)	 18Kg
		 Ancho Ø520 mm Largo mm Alto 850 mm

Tolerancias: +-7% flujo LED / +- 10% potencia luminaria

CURVAS

