























# URA ERALIGHT


**Ref: S3491029074ERA3406**
**URA ERALIGHT 90W 4000K LED NEGRO SIM EXT 160º ON/OFF**

 EXTERIOR	 81 W LED 90 W Sistema	 11108 lm LED 10099 lm Sistema
 SUPERFICIE	 Driver incluido (SPD10KV)	 0
 Garantía 5 AÑOS	 ON/OFF	 mm
	 IP65	 70
	 08	 I
 MIDPOWER	 SIM EXT 160	 L80B10 50000h 85°C L70B50 70000h 85°C
 220-240V	 4000K	 -20º+35°C
 50-60Hz	 0 (Riesgo fotobiológico)	 18Kg



Ancho 440 mm

Largo 440 mm

Alto 740 mm

Tolerancias: +-7% flujo LED / +- 10% potencia luminaria

## CURVAS



www.secom.es



P. I. la Estrella  
C. Marte 18/21 - 30500 Molina de Segura  
Murcia - Spain  
T. +34 968 80 12 11

